

## GROUP D



## 208/240/277/380/480 PRIMARY VOLTS—24 SECONDARY VOLTS—1Ø, 50/60 Hz

| CATALOG NO. | VA RATING | OUTPUT AMPS | APPROX. DIMENSIONS INCHES (CM.) |                |                |                |                |                          | APPROX. SHIP WEIGHT LBS. (KG.) | PRIMARY FUSE BLOCK PART NO. | SECONDARY FUSE KIT ① PART NO. | SECONDARY FUSE SIZE 24 VOLTS       |
|-------------|-----------|-------------|---------------------------------|----------------|----------------|----------------|----------------|--------------------------|--------------------------------|-----------------------------|-------------------------------|------------------------------------|
|             |           |             | A                               | B              | C              | D              | E              | F                        |                                |                             |                               |                                    |
| TB81321     | 50        | 2.08        | 4.08<br>(10.4)                  | 3.75<br>(9.5)  | 3.40<br>(8.6)  | 3.13<br>(8.0)  | 2.19<br>(5.6)  | .22 x .50<br>(0.6 x 1.3) | 4<br>(1.8)                     | PL112701                    | ★                             | 3 <sup>2</sup> / <sub>10</sub> amp |
| TB81322     | 75        | 3.13        | 4.31<br>(10.9)                  | 3.75<br>(9.5)  | 3.40<br>(8.6)  | 3.13<br>(8.0)  | 2.31<br>(5.9)  | .22 x .50<br>(0.6 x 1.3) | 5<br>(2.3)                     | PL112701                    | ★                             | 5 amps                             |
| TB81323     | 100       | 4.17        | 4.52<br>(11.5)                  | 3.75<br>(9.5)  | 3.40<br>(8.6)  | 3.13<br>(8.0)  | 2.63<br>(6.7)  | .22 x .50<br>(0.6 x 1.3) | 5<br>(2.3)                     | PL112701                    | ★                             | 6 <sup>1</sup> / <sub>4</sub> amps |
| TB81324     | 150       | 6.25        | 4.75<br>(12.1)                  | 4.50<br>(11.4) | 3.84<br>(9.8)  | 3.75<br>(9.5)  | 3.05<br>(7.7)  | .22 x .50<br>(0.6 x 1.3) | 9<br>(4.1)                     | PL112702                    | ★                             | 10 amps                            |
| TB81325     | 250       | 10.42       | 5.24<br>(13.3)                  | 4.65<br>(11.8) | 4.15<br>(10.5) | 4.06<br>(10.3) | 3.25<br>(8.3)  | .22 x .50<br>(0.6 x 1.3) | 11<br>(5.0)                    | PL112702                    | ★                             | 15 amps                            |
| TB81326     | 350       | 14.58       | 6.02<br>(15.3)                  | 5.25<br>(13.3) | 4.47<br>(11.4) | 4.38<br>(11.1) | 4.00<br>(10.2) | .31 x .50<br>(0.8 x 1.3) | 18<br>(8.2)                    | PL112704                    | ★                             | 20 amps                            |
| TB81327     | 500       | 20.83       | 6.51<br>(16.5)                  | 5.25<br>(13.3) | 4.47<br>(11.4) | 4.38<br>(11.1) | 4.19<br>(10.6) | .31 x .50<br>(0.8 x 1.3) | 19<br>(8.6)                    | PL112704                    | ★                             | 30 amps                            |
| TB81328     | 750       | 31.25       | 7.08<br>(18.0)                  | 6.75<br>(17.1) | 5.78<br>(14.7) | 5.75<br>(14.6) | 3.81<br>(9.7)  | .31 x .50<br>(0.8 x 1.3) | 26<br>(11.8)                   | PL112705                    | ★                             | —<br>33 amps                       |
| TB81329     | 1000      | 41.67       | 8.10<br>(20.6)                  | 6.75<br>(17.1) | 5.72<br>(14.5) | 5.75<br>(14.6) | 4.63<br>(11.8) | .31 x .50<br>(0.8 x 1.3) | 33<br>(15.0)                   | PL112705                    | ★                             | —                                  |

★ See fusing chart for secondary fuse kits.

## GROUP E

## 208/277/380 PRIMARY VOLTS—115/95 SECONDARY VOLTS—1Ø, 50/60 Hz

| CATALOG NO. | VA RATING | OUTPUT AMPS @ 115V | APPROX. DIMENSIONS INCHES (CM.) |                |                |                |                |                          | APPROX. SHIP WEIGHT LBS. (KG.) | PRIMARY FUSE BLOCK PART NO. | SECONDARY FUSE KIT ① PART NO. | SECONDARY FUSE SIZE 115 VOLTS      |
|-------------|-----------|--------------------|---------------------------------|----------------|----------------|----------------|----------------|--------------------------|--------------------------------|-----------------------------|-------------------------------|------------------------------------|
|             |           |                    | A                               | B              | C              | D              | E              | F                        |                                |                             |                               |                                    |
| TB81301     | 50        | 0.43               | 4.35<br>(11.0)                  | 3.00<br>(7.6)  | 2.70<br>(6.8)  | 2.50<br>(6.4)  | 2.61<br>(6.6)  | .22 x .50<br>(0.6 x 1.3) | 4<br>(1.8)                     | PL112700                    | ★                             | 6 <sup>1</sup> / <sub>10</sub> amp |
| TB81302     | 75        | 0.65               | 4.74<br>(12.0)                  | 3.00<br>(7.6)  | 2.70<br>(6.8)  | 2.50<br>(6.4)  | 2.81<br>(7.1)  | .22 x .50<br>(0.6 x 1.3) | 4<br>(1.8)                     | PL112700                    | ★                             | 1 amp                              |
| TB81303     | 100       | 0.87               | 4.45<br>(11.3)                  | 3.75<br>(9.5)  | 3.40<br>(8.6)  | 3.13<br>(8.0)  | 2.44<br>(6.2)  | .22 x .50<br>(0.6 x 1.3) | 5<br>(2.3)                     | PL112701                    | ★                             | 1 <sup>1</sup> / <sub>4</sub> amps |
| TB81304     | 150       | 1.30               | 5.00<br>(12.7)                  | 3.75<br>(9.5)  | 3.84<br>(9.8)  | 3.13<br>(8.0)  | 3.06<br>(7.8)  | .22 x .50<br>(0.6 x 1.3) | 5<br>(2.3)                     | PL112701                    | ★                             | 2 amps                             |
| TB81305     | 250       | 2.17               | 5.68<br>(14.4)                  | 4.50<br>(11.4) | 3.84<br>(9.8)  | 3.75<br>(9.5)  | 4.06<br>(10.3) | .22 x .50<br>(0.6 x 1.3) | 13<br>(5.9)                    | PL112702                    | ★                             | 3 <sup>1</sup> / <sub>2</sub> amps |
| TB81306     | 350       | 3.04               | 6.30<br>(16.0)                  | 4.65<br>(11.8) | 4.15<br>(10.5) | 4.06<br>(10.3) | 4.75<br>(12.1) | .22 x .50<br>(0.6 x 1.3) | 18<br>(8.2)                    | PL112702                    | ★                             | 5 amps                             |
| TB81307     | 500       | 4.35               | 6.22<br>(15.8)                  | 5.25<br>(13.3) | 4.47<br>(11.4) | 4.38<br>(11.1) | 4.56<br>(11.6) | .22 x .50<br>(0.6 x 1.3) | 20<br>(9.1)                    | PL112704                    | ★                             | 7 amps                             |
| TB81308     | 750       | 6.52               | 6.82<br>(17.3)                  | 6.75<br>(17.1) | 5.78<br>(14.7) | 5.75<br>(14.6) | 3.69<br>(9.4)  | .31 x .50<br>(0.8 x 1.3) | 24<br>(10.9)                   | PL112705                    | ★                             | 10 amps                            |
| TB81309     | 1000      | 8.70               | 7.96<br>(20.2)                  | 6.75<br>(17.1) | 5.72<br>(14.5) | 5.75<br>(14.6) | 4.44<br>(11.3) | .31 x .50<br>(0.8 x 1.3) | 31<br>(14.1)                   | PL112705                    | ★                             | 12 amps                            |

★ See fusing chart for secondary fuse kits.

① Secondary Fuse Kit PL112603 may be substituted for PL112600 thru PL112602 when Primary Fuse Kit is used. See page 62.

② See chart for integrally mounted fuse block catalog number suffix.